

USER'S MANUAL

PA-3252

**15" POS System Powered by
Intel® Atom® D525 Platform**

PA-3252 M1

PA-3252 POS System ***With LCD / Touchscreen***

PREFACE

COPYRIGHT NOTICE

This user's manual is meant to assist users in installing and setting up the system. The information contained in this document is subject to change without any notice.

This manual is copyrighted May 2012. You may not reproduce or transmit in any form or by any means, electronic, or mechanical, including photocopying and recording.

ACKNOWLEDGEMENTS

All trademarks and registered trademarks mentioned herein are the property of their respective owners.

CE NOTICE

This is a class A product. In a domestic environment this product may cause radio interference in which case the user may be required to take adequate measures.

FCC NOTICE

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

You are cautioned that any change or modifications to the equipment not expressly approve by the party responsible for compliance could void your authority to operate such equipment.

CAUTION!

Danger of explosion if battery is incorrectly replaced. Replace only with the same or equivalent type recommended by the manufacturer. Dispose of used batteries according to the manufacturer's instructions.

WARNING!

Some internal parts of the system may have high electrical voltage. And therefore we strongly recommend that qualified engineers can open and disassemble the system. The LCD and Touchscreen are easily breakable, please handle them with extra care.

TABLE OF CONTENTS

CHAPTER 1 INTRODUCTION

1-1	About This Manual	1-2
1-2	POS System Illustration	1-3
1-3	System Specification	1-4
1-4	Safety Precautions	1-7

CHAPTER 2 SYSTEM CONFIGURATION

2-1	Jumper & Connector Quick Reference Table	2-2
2-2	Component Locations	2-3
2-3	How to Set the Jumpers	2-4
2-4	COM Port & VGA Connector	2-6
2-5	COM Port RI and Voltage Selection	2-9
2-6	Mini-DIN and USB Connector	2-13
2-7	LAN & USB Connector	2-14
2-8	Cash Drawer Connector	2-15
2-9	Cash Drawer Power Selection	2-16
2-10	Power LED Connector	2-17
2-11	Smart FAN Connector	2-17
2-12	Power Connector	2-17
2-13	Reset Switch Connector	2-18
2-14	Power for Thermal Printer Connector	2-18
2-15	External Speaker Connector	2-18
2-16	Inverter Connector	2-19
2-17	MSR/ Card Reader Connector	2-19
2-18	Printer Connector	2-20
2-19	LVDS Connector	2-21
2-20	SATA Connector	2-23
2-21	SATA Power Connector	2-23
2-22	Touch Panel Connector	2-24
2-23	Touch Panel Selection	2-24
2-24	Clear CMOS Data Selection	2-25
2-25	Compact Flash Connector	2-26

CHAPTER 3 SOFTWARE UTILITIES

3-1	Introduction	3-2
3-2	Intel® Chipset Software Installation Utility	3-3
3-3	VGA Driver Utility	3-4
3-4	LAN Driver Utility	3-5
3-5	Sound Driver Utility	3-6

CHAPTER 4 AMI BIOS SETUP

4-1	Introduction	4-2
4-2	Entering Setup	4-3
4-3	Main	4-5
4-4	Advanced	4-6
4-5	Boot	4-16
4-6	Security Settings	4-20
4-7	Chipset	4-21
4-8	Exit	4-25

APPENDIX A SYSTEM ASSEMBLY

Exploded Diagram for PA-3252 Top Case	A-3
Exploded Diagram for PA-3252 Open & Close	A-4
Exploded Diagram for PA-3252 Bottom Case	A-5
Exploded Diagram for PA-3252 Inside Box	A-6
Exploded Diagram for PA-3252 CPU Cooler	A-8
Exploded Diagram for PA-3252 LCD Panel	A-9
Exploded Diagram for PA-3252 Printer Box	A-11
Exploded Diagram for PA-3252 2 Inch Printer	A-12
Exploded Diagram for PA-3252 2 Inch Printer Cover	A-14
Exploded Diagram for PA-3252 3 Inch Printer	A-15
Exploded Diagram for PA-3252 3 Inch Printer Cover	A-17
Exploded Diagram for PA-3252 Printer Control Board	A-18
Exploded Diagram for PA-3252 Hard Disk Drive	A-20
Exploded Diagram for PA-3252 VFD Cover	A-21
Exploded Diagram for PA-3252 SSD Module	A-23
Exploded Diagram for PA-3252 RFID Module	A-24
Exploded Diagram for PA-3252 Memory Maintenance	A-26
Exploded Diagram for PA-3252 Mini PCIE and CF Card Maintenance	A-27

Exploded Diagram for PA-3252 2 Inch Printer Maintenance ...	A-29
Exploded Diagram for PA-3252 3 Inch Printer Maintenance ...	A-30
Exploded Diagram for PA-3252 Printer Platen Block Maintenance	A-31

APPENDIX B TECHNICAL SUMMARY

Block Diagram	B-2
Interrupt Map	B-3
DMA Channels Map	B-4
I/O Map	B-5
Watchdog Timer Configuration	B-8
Flash BIOS Update	B-10



INTRODUCTION

CHAPTER

1

This chapter gives you the information for PA-3252. It also outlines the system specifications.

Sections included:

- About This Manual
- POS System Illustration
- System Specifications
- Safety Precautions

Experienced users can jump to chapter 2 on page 2-1 for a quick start.

1-1. ABOUT THIS MANUAL

Thank you for purchasing our PA-3252 system. The PA-3252 is an updated system designed to be comparable with the highest performance of IBM AT personal computers. The PA-3252 provides faster processing speed, greater expandability and can handle more tasks than before. This manual is designed to assist you how to install and set up the whole system. It contains four chapters and two appendixes. Users can configure the system according to their own needs.

Chapter 1 Introduction

This chapter introduces you to the background of this manual. It also includes illustrations and specifications for the whole system. The final section of this chapter indicates some safety reminders on how to take care of your system.

Chapter 2 System Configuration

This chapter outlines the location of motherboard components and their function. You will learn how to set jumper and how to configure the system to meet your own needs.

Chapter 3 Software Utilities

This chapter contains helpful information for proper installations of the Intel Utility, VGA Utility, LAN Utility, Sound Utility, and Touch Screen Utility.

Chapter 4 AMI BIOS Setup

This chapter indicates you how to change the BIOS configurations.

Appendix A System Assembly


This appendix gives you the exploded diagrams and part numbers of the PA-3252.

Appendix B Technical Summary


This appendix gives you the information about the allocation maps for the system resources, Watchdog Timer Configuration, and Flash BIOS Update.

1-2. POS SYSTEM ILLUSTRATION


Front View



Rear View



Side View



1-3. SYSTEM SPECIFICATIONS

MAINBOARD (PROX3520LF)

- **CPU Type:**
Intel® ATOM D525
- **Chipset:**
Intel® ICH8M
- **Memory:**
One 204-pin DDRIII SO-DIMM socket on board, up to 2GB
- **Cache:**
Depends on CPU
- **Real-Time Clock / Calendar:**
Embedded in Intel® ICH8M South Bridge
- **BIOS:**
AMI SPI BIOS
8Mbits with VGA BIOS
- **Keyboard Connector:**
PS/2 Keyboard, with mini DIN connector on rear panel.
- **Mouse Connector:**
PS/2 Mouse, with mini DIN connector on rear panel.
- **Serial Port:**
3 x DB-9 (COM 1/2/4)
1 x RJ45 (COM3)
+5/12V Selectable (COM 1~3)
- **Universal Serial BUS Port:**
4 x USB2.0 ports
1 x USB2.0 on side bezel

- **LAN Function:**
1 x 10/100/1000 Mbps
- **Audio Function:**
1 x 2W Speaker
- **VGA Function:**
1 x DB-15 VGA Interface
- **Dimension (W x H x D):**
300mm x 299mm x 135mm
- **System Weight:**
4.5kg
- **LCD Panel:**

Type	XGA/SVGA
Max. Resolution	1024 x 768 / 800 x 600
Size/Type	10.4" / TFT
Viewing Angel (degree)	0~65 degrees
Pixel Pitch	0.206(W) x 0.206(H)/ 0.088(W) x 0.264(H)
Brightness	300 / 230 cd / m ²
Signal Interface (bit)	TTL (18-bit)
LCD MTBF	20,000
Back Light MTBF (Hrs)	20,000

- **Touch Panel:**
10.4" 5wire Analog resistive.
- **Printer:**
2" or 3" easy loading thermal printer with Auto cutter (* Diameter of paper roll can not exceed 8 cm.)
- **I-Button (optional):**
Read only, output through PS/2 KB interface

- **MSR (optional):**
JIS-I or II, ISO Tracker 1+2+3 (PS/2 KB Interface)
- **Wireless LAN (optional):**
Mini PCIe Wireless LAN Module (802.11b/g)
- **Fingerprint (optional):**
Embedded Fingerprint module (USB Interface)
- **RFID (optional):**
Read/ Write, ISO 14443A 13.56MHz (USB Interface)

1-4. SAFETY PRECAUTIONS

The following messages are safety reminders on how to protect your systems from damages, and extending the life cycle of the system.

1. Check the Line Voltage

- a. The operating voltage for the power supply should be within the range of 100V to 240V AC; otherwise the system may be damaged.

2. Environmental Conditions

- a. Place your PA-3252 on a sturdy, level surface. Be sure to allow enough space around the system to have easy access needs.
- b. Avoid installing your PA-3252 system in extremely hot or cold places.
- c. Avoid exposure to sunlight for a long period of time (for example, in a closed car in summer time. Also avoid the system from any heating device.). Or do not use the PA-3252 when it has been left outdoors in a cold winter day.
- d. Bear in mind that the operating ambient temperature is between 0°C and 35°C (32°F and 95°F).
- e. Avoid moving the system rapidly from a hot place to a cold place, and vice versa, because condensation may occur inside the system.
- f. Place your PA-3252 against strong vibrations, which may cause hard disk failure.
- g. Do not place the system too close to any radio-active device. Radio-active device may cause signal interference.
- h. Always shutdown the operation system before turning off the power.


3. Handling

- a. Avoid placing heavy objects on the top of the system.
- b. Do not turn the system upside down. This may cause the hard drive to malfunction.
- c. Do not allow any objects to fall into this product.
- d. If water or other liquid spills into the product, unplug the power cord immediately.

4. Good Care

- a. When the outside case gets stained, remove the stains using neutral washing agent with a dry cloth.
- b. Never use strong agents such as benzene and thinner to clean the surface of the case.
- c. If heavy stains are present, moisten a cloth with diluted neutral washing agent or alcohol and then wipe thoroughly with a dry cloth.
- d. If dust is accumulated on the case surface, remove it by using a special vacuum cleaner for computers.

SYSTEM CONFIGURATION



Helpful information that describes the jumper and connector settings, and component locations.


Sections included:

- Jumper & Connector Quick Reference Table
- Component Locations
- Configuration and Jumper settings
- Connector Pin Assignments

2-1. JUMPER & CONNECTOR QUICK REFERENCE TABLE

CONNECTOR/JUMPER	NAME	PAGE
COM Port & VGA Connector	COM1, COM3, COM4, COM2-1, JVGACOM2	2-6
COM Port RI and Voltage Selection	JP_COM1, JP_COM2, JP_COM3, JP_COM4	2-9
MINI-DIN and USB Connector	JPS2USB1, USB5, USB6	2-13
LAN & USB Connector	JRJ45USB1	2-14
Cash Drawer Connector	DRW1, DRW2	2-15
Cash Drawer Power Selection	JP14, JP17	2-16
Power LED Connector	LED-1	2-17
Smart Fan Connector	FAN2	2-17
Power Connector	FAN1	2-17
Reset Switch Connector	JRST1	2-18
Power for Thermal printer Connector	PRT_PWR1	2-18
External Speaker Connector	SPK1	2-18
Inverter Connector	INV1, INV2	2-19
MSR/ Card Reader Connector	PS2	2-20
Printer Connector	LPT1	2-20
LVDS Connector	LVDS1, LVDS2	2-21
SATA Connector	SATA1	2-23
SATA Power Connector	JPWR_4P1	2-23
Touch Panel Connector	TOUCH1	2-24
Touch Panel Selection	JP16	2-24
Clear CMOS Data Selection	JP1	2-25
Compact Flash Connector	CF1	2-26

2-2. COMPONENT LOCATIONS




PA-3252 Connector, Jumper and Component locations

2-3. HOW TO SET THE JUMPERS

You can configure your board by setting the jumpers. Jumper is consists of two or three metal pins with a plastic base mounted on the card, and by using a small plastic "cap", Also known as the jumper cap (with a metal contact inside), you are able to connect the pins. So you can set-up your hardware configuration by "opening" or "closing" pins.

The jumper can be combined into sets that called jumper blocks. When the jumpers are all in the block, you have to put them together to set up the hardware configuration. The figure below shows how this looks like.

JUMPERS AND CAPS




If a jumper has three pins for example, labelled PIN1, PIN2, and PIN3. You can connect PIN1 & PIN2 to create one setting and shorting. You can either connect PIN2 & PIN3 to create another setting. The same jumper diagrams are applied all through this manual. The figure below shows what the manual diagrams look and what they represent.


JUMPER DIAGRAMS





Jumper Cap looks like this




2 pin Jumper looks like this



3 pin Jumper looks like this



Jumper Block looks like this



JUMPER SETTINGS




2 pin Jumper closed(enabled)
looks like this



1

1



3 pin Jumper
2-3 pin closed(enabled)
looks like this




1

1



Jumper Block
1-2 pin closed(enabled)
looks like this



1 2

1 2

2-4. COM PORT & VGA CONNECTOR


There are four COM ports enhanced in this board namely: COM1, COM2, COM3 and COM4.

Caution: When using a 72W power adaptor, do not set the voltage at “12V” for three COM ports or above; otherwise, the system may shut down due to power deficiency.

COM1: COM1 Connector

The COM1 Connector assignments are as follows:

PIN	ASSIGNMENT
1	DCD2
2	RXD2
3	TXD2
4	DTR2
5	GND
6	DSR2
7	RTS2
8	CTS2
9	RI / +5V / +12V selectable




COM1

COM3: COM3 Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	DCD3
2	RXD3
3	TXD3
4	DTR3
5	GND
6	DSR3
7	RTS3
8	CTS3
9	RI / +5V / +12V selectable
10	NC



COM3

COM4: COM4 Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	DCD4
2	RXD4
3	TXD4
4	DTR4
5	GND
6	DSR4
7	RTS4
8	CTS4
9	RI / +5V / +12V selectable
10	NC



COM2-1: COM2 External Connector

The pin assignments are as follows:


PIN	ASSIGNMENT
1	DCD1
2	RXD1
3	TXD1
4	DTR1
5	GND
6	DSR1
7	RTS1
8	CTS1
9	RI / +5V / +12V selectable
10	NC



JVGACOM2: COM2 & VGA Connector

The COM2 & VGA Connector assignments are as follows:

PIN	ASSIGNMENT
1	RED
2	GREEN
3	BLUE
4	NC
5	GND
6	GND
7	GND
8	GND
9	+5V
10	GND
11	NC
12	DDCA DATA
13	HSYNC
14	VSYNC
15	DDCA CLK
16	DCD1
17	RXD1
18	TXD1
19	DTR1
20	GND
21	DSR1
22	RTS1
23	CTS1
24	RI / +5V / +12V selectable






Note: All COM port is selectable for RI, +5V or +12V. For more information, please refer to our “COM RI and Voltage Selection”.

2-5. COM PORT RI & VOLTAGE SELECTION

Caution: When using a 72W power adaptor, do not set the voltage at “12V” for three COM ports or above; otherwise, the system may shut down due to power deficiency.

JP_COM1: COM1 RI & Voltage Selection




The selections are as follows:

SELECTION	JUMPER SETTINGS	JUMPER ILLUSTRATION
RI	1-2	 <p style="text-align: center;">JP_COM1</p>
VCC12	3-4	 <p style="text-align: center;">JP_COM1</p>
VCC	5-6	 <p style="text-align: center;">JP_COM1</p>

Note: Manufacturing Default – RI

JP_COM2: COM2 RI & Voltage Selection




The selections are as follows:

SELECTION	JUMPER SETTINGS	JUMPER ILLUSTRATION
RI	1-2	 <p>JP_COM2</p>
VCC12	3-4	 <p>JP_COM2</p>
VCC	5-6	 <p>JP_COM2</p>

Note: Manufacturing Default – RI

JP_COM3: COM3 RI & Voltage Selection




The selections are as follows:

SELECTION	JUMPER SETTINGS	JUMPER ILLUSTRATION
RI	1-2	 <p>JP_COM3</p>
VCC12	3-4	 <p>JP_COM3</p>
VCC	5-6	 <p>JP_COM3</p>

Note: Manufacturing Default – RI

JP_COM4: COM4 RI & Voltage Selection

The selections are as follows:

SELECTION	JUMPER SETTINGS	JUMPER ILLUSTRATION
RI	1-2	 <p>JP_COM4</p>
VCC12	3-4	 <p>JP_COM4</p>
VCC	5-6	 <p>JP_COM4</p>

Note: Manufacturing Default – RI


2-6. MINI-DIN AND USB CONNECTOR

JPS2USB1: Two USB Ports Connector and MINI-DIM

MINI-DIN connector can support keyboard, Y-cable, or PS/2 Mouse.

The pin assignments are as follows:

PIN	ASSIGNMENT
1	GND
2	USB2+
3	USB2-
4	VCC5
5	GND
6	USB3+
7	USB3-
8	VCC5
9	GND
10	KDAT
11	MDAT
12	V5SB
13	KCLK
14	MCLK



JPS2USB1

USB5: Internal USB Ports Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	USB5-
2	USB5+
3	GND
4	VCC5
5	GND




USB5

USB6: Internal USB Ports Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	USB6-
2	USB6+
3	GND
4	VCC5
5	GND




2-7. LAN & USB CONNECTOR

JRJ45USB1: LAN & USB Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	LAN1_MDIP0
2	LAN1_MDIN0
3	LAN1_MDIP1
4	LAN1_MDIN1
5	LAN1_MDIP2
6	LAN1_MDIN2
7	LAN1_MDIP3
8	LAN1_MDIN3
A1	VCC5
A2	USB0-
A3	USB0+
A4	GND
B1	VCC5
B2	USB1-
B3	USB1+
B4	GND




2-8. CASH DRAWER CONNECTOR


DRW1, DRW2: Cash Drawer Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	GND
2	Drawer Open
3	Drawer Sense
4	+12V
5	NC
6	GND



DRW1



DRW2

PA-3252 cash drawer control in GPIO port

To Open Drawer1 (GPIO 7)

Write "0" to I/O space register "50C" Bit 7

To Close Drawer1

Write "1" to I/O space register "50C" Bit 7

Detect Drawer1 Status

Read I/O space register "50E" (GPIO 20)

Definition (bit4)

To Open Drawer2 (GPIO 6)

Write "0" to I/O space register "50C" Bit 6

To Close Drawer2

Write "1" to I/O space register "50C" Bit 6

Detect Drawer2 Status





Read I/O space register "538" (GPIO 37)

Definition (bit5)

2-9. CASH DRAWER POWER SELECTION

JP14, JP17: Cash Drawer Power Selection

The jumper settings are as follows:

SELECTION	JUMPER SETTINGS	JUMPER ILLUSTRATION
+12V	2-3	 JP14  JP17
+24V	1-2	 JP14  JP17


Note: Manufactory default – +24V

2-10. POWER LED CONNECTOR

LED-1: LED Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	GND
2	VCC_PWR_LED




2-11. SMART FAN CONNECTOR

FAN2: CPU Smart Fan Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	GND
2	12V
3	CPUFANIN
4	CPUFANOUT




2-12. POWER CONNECTOR

FAN1: Provide 12 Voltage Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	VCC12
2	GND




2-13. RESET SWITCH CONNECTOR

RST_SW1: Power Switch Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	RST_SW
2	GND




2-14. POWER FOR THERMAL PRINTER CONNECTOR

PRT_PWR1: Power for Thermal printer Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	VCC24SB
2	VCC24SB
3	GND
4	GND



2-15. EXTERNAL SPEAKER CONNECTOR

SPK1: External Speaker Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	SPK_GND
2	SPK_OUT



2-16. INVERTER CONNECTOR

INV1: Inverter Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	+12V
2	+12V
3	GND
4	GND
5	LVDS_BKLTEN
6	BRCTR
7	GND



INV1

INV2: Inverter Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	+12V
2	GND
3	LVDS_BKLTEN
4	BRCTR



INV2

2-17. MSR/ CARD READER CONNECTOR

PS2: MSR/ Card Reader Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	KB_CLK (Output)
2	KB_CLK_C (Input)
3	KB_DATA_C (Input)
4	KB_DATA (Output)
5	+5V
6	GND




PS2

2-18. PRINTER CONNECTOR

LPT1: LPT Connector.

The assignments are as follows:




LPT1

PIN	ASSIGNMENT	PIN	ASSIGNMENT
1	STBJ	14	ALFJ
2	PDR0	15	ERRJ
3	PDR1	16	PAR_INITJ
4	PDR2	17	SLCTINJ
5	PDR3	18	GND
6	PDR4	19	GND
7	PDR5	20	GND
8	PDR6	21	GND
9	PDR7	22	GND
10	ACKJ	23	GND
11	BUSY	24	GND
12	PE	25	GND
13	SLCTJ	26	NC

2-19. LVDS CONNECTOR

LVDS1: LVDS Connector.


The pin assignments are as follows:



LVDS1

PIN	ASSIGNMENT	PIN	ASSIGNMENT
1	GND	2	LVDS_VCC
3	LVDS_YAP2	4	LVDS_VCC
5	LVDS_YAM2	6	GND
7	GND	8	GND
9	LVDS_YAP1	10	LVDS_CLKAP
11	LVDS_YAM1	12	LVDS_CLKAM
13	GND	14	GND
15	LVDS_YAP0	16	GND
17	LVDS_YAM0	18	LVDS_VCC
19	GND	20	LVDS_VCC

LVDS2: LVDS Connector.
 The pin assignments are as follows:



LVDS2


PIN	ASSIGNMENT	PIN	ASSIGNMENT
1	LVDS_VCC	2	GND
3	NC	4	NC
5	GND	6	NC
7	NC	8	GND
9	NC	10	NC
11	NC	12	NC
13	NC	14	NC
15	GND	16	CLKO+
17	CLKO-	18	GND
19	RINO2+	20	RINO2-
21	GND	22	RINO1+
23	RINO1-	24	GND
25	RINO0+	26	RINO0-
27	NC	28	NC
29	LVDS_VCC	30	LVDS_VCC

2-20. SATA CONNECTOR

SATA1: Serial ATA Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	G1
2	TX+
3	TX-
4	G2
5	RX-
6	RX+
7	G3



SATA1

2-21. SATA POWER CONNECTOR

JPWR_4P1: Serial ATA Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	VCC
2	GND
3	GND
4	VCC12




JPWR_4P1

2-22. TOUCH PANEL CONNECTOR

TOUCH1: Touch Panel Connector

The pin assignments are as follows:

PIN	ASSIGNMENT
1	LR (Low Right)
2	LL (Low Left)
3	Probe
4	UR (Up Right)
5	UL (Up Left)



2-23. TOUCH PANEL SELECTION

JP16: Touch Panel Selection

The selections are as follows:



SELECTION	JUMPER SETTINGS	JUMPER ILLUSTRATION
e-Turbo	1-2 5-6	<p>JP16</p>
Elo	3-4 7-8	<p>JP16</p>

Note: Manufactory default – Elo

2-24. CLEAR CMOS DATA SELECTION

JP1: Clear CMOS Data Selection

The selections are as follows:

SELECTION	JUMPER SETTINGS	JUMPER ILLUSTRATION
Normal	1-2	 <p>1 3 JP1</p>
Clear CMOS*	2-3	 <p>1 3 JP1</p>

Note: Manufacturing Default – Normal

*To clear CMOS data, user must power-off the computer and set the jumper to “Clear CMOS” as illustrated above. After five to six seconds, set the jumper back to “Normal” and power-on the computer.

2-25. COMPACT FLASH CONNECTOR

CF1: Compact Flash Connector

The pin assignments are as follows:

PIN	ASSIGNMENT	PIN	ASSIGNMENT
1	GND	26	GND
2	D03	27	D11
3	D04	28	D12
4	D05	29	D13
5	D06	30	D14
6	D07	31	D15
7	CSJ1	32	CSJ3
8	GND	33	GND
9	GND	34	SDIORDJ
10	GND	35	SDIOWRJ
11	GND	36	+5V
12	GND	37	IRQ14
13	+5V	38	+5V
14	GND	39	-CSEL
15	GND	40	NC
16	GND	41	RESETJ
17	GND	42	IORDJ
18	A02	43	REQ
19	A01	44	ACKJ
20	A00	45	CF_LEDJ
21	D00	46	-PDIAG
22	D01	47	D08
23	D02	48	D09
24	NC	49	D10
25	GND	50	GND

SOFTWARE UTILITIES

CHAPTER **3**

This chapter provides the detailed information users need to install driver utilities for the system.

Sections included:

- Intel® Chipset Software Installation Utility
- VGA Driver Utility
- LAN Driver Utility
- Sound Driver Utility
- Touch Screen Driver Utility
- Wireless Driver Utility (Optional)

3-1. INTRODUCTION

Enclosed with the PA-3252 Series package is our driver utilities, which comes in a CD ROM format. Refer to the following table for driver locations.

FILE NAME (Assume that CD ROM drive is D:)	PURPOSE
D:\Driver\Plaform\Win7,POSReady7(32-bit)\Main Chip	Intel® Chipset Software Installation Utility
D:\Driver\Plaform\WinXP,POSReady2009 (32-bit)\Main Chip	Intel® Graphics Media Accelerator 3150
D:\Driver\Plaform\Win7,POSReady7(32-bit)\VGA	Realtek® ALC888 High Definition Audio Codecs for Sound driver installation
D:\Driver\Plaform\WinXP,POSReady2009 (32-bit)\VGA	Realtek® RTL8111DL for LAN driver installation
D:\Driver\Plaform\Win7,POSReady7(32-bit)\Sound	For BIOS update utility (AMI)

Note: Be sure to install the driver utilities right after the OS is fully installed.

3-2. INTEL® CHIPSET SOFTWARE INSTALLATION UTILITY

3-2-1. Introduction

The Intel® Chipset Software Installation Utility installs to the target system the Windows* INF files that outline to the operating system how the chipset components will be configured. This is needed for the proper functioning of the following features:

- Core PCI and ISAPNP Services
- AGP Support
- SATA Storage Support
- USB Support
- Identification of Intel® Chipset Components in Device Manager


3-2-2. Installation of Intel® Chipset Driver

The utility pack is to be installed only for Windows XP/ 7 series, and it should be installed right after the OS installation. Please follow the steps below:

1. Connect the USB-CD ROM device to the PA-3252 and insert the driver disk inside.
2. Enter the “Main Chip” folder where the Chipset driver is located (depending on your OS platform).
3. Click Setup.exe file for driver installation.
4. Follow the on-screen instructions to complete the installation.
5. Once installation is completed, shut down the system and restart the PA-3252 for the changes to take effect.

3-3. VGA DRIVER UTILITY

The VGA interface embedded with the PA-3252 series can support a wide range of display types. You can have dual displays via CRT and LVDS interfaces work simultaneously.




3-3-1. Installation of VGA Driver

To install the VGA Driver, follow the steps below:

1. Connect the USB-CD ROM device to the PA-3252 and insert the driver disk inside.
2. Enter the "VGA" folder where the VGA driver is located (depending on your OS platform).
3. Click Setup.exe file for driver installation.
4. Follow the on-screen instructions to complete the installation.
5. Once installation is completed, shut down the system and restart the PA-3252 for the changes to take effect.

3-4. LAN DRIVER UTILITY

The PA-3252 Series is enhanced with LAN function that can support various network adapters. Installation platform for the LAN driver is listed as follows:



For more details on the Installation procedure, please refer to the Readme.txt file found on LAN Driver Utility.


3-4-1. Installation of LAN Driver

To install the LAN Driver, follow the steps below:

1. Connect the USB-CD ROM device to the PA-3252 and insert the driver disk inside.
2. Enter the "LAN" folder where the LAN driver is located (depending on your OS platform).
3. Click Setup.exe file for driver installation.
4. Follow the on-screen instructions to complete the installation.
5. Once installation is completed, shut down the system and restart the PA-3252 for the changes to take effect.

3-5. SOUND DRIVER UTILITY

The sound function enhanced in this system is fully compatible with Windows XP/7 series. Below, you will find the content of the Sound driver.



3-5-1. Installation of Sound Driver

To install the Sound Driver, refer to the readme.txt file on the driver disc (:\\Sound\\Realtek\\Readme.txt).

1. Connect the USB-CD ROM device to the PA-3252 and insert the driver disk inside.
2. Enter the “Sound” folder where the Sound driver is located (depending on your OS platform).
3. Click Setup.exe file for driver installation.
4. Follow the on-screen instructions to complete the installation.
5. Once installation is completed, shut down the system and restart the PA-3252 for the changes to take effect.

AMI BIOS SETUP

CHAPTER

4

This chapter shows how to configure the AMI BIOS settings.

Sections included:

- Introduction
- Entering Setup
- Main
- Advanced
- Boot
- Security
- Chipset
- Exit

4-1. INTRODUCTION


This chapter will show you the function of the BIOS (Basic Input and Output System) in managing the features of your system. The PA-3252 POS Terminal is equipped with the BIOS from AMI (American Megatrends Inc). The following pages describe how to use the BIOS for configure system hardware by BIOS Setup menu.

When the PC starts up, the first job for the BIOS is to initialize and identify system devices such as the video display card, keyboard and mouse, hard disk, CD/DVD drive and other hardware. The BIOS then locates software held on a peripheral device (designated as a 'boot device'), such as a hard disk or a CD, and loads and executes that software, giving it control of the PC.

BIOS code is stored on a non-volatile, ROM chip built into the system, on the mother board and the BIOS software is specifically designed to work with the particular type of system in question including having a knowledge of the workings of various devices that make up the complementary chipset of the system


BIOS also provide a user interface, this is a menu system accessed by pressing a certain key on the keyboard when the PC starts. In the BIOS UI, a user can configure hardware, set the system clock, enable or disable system components, and most importantly, select which devices are eligible to be a potential boot device and set various password prompts, most importantly a password for securing access to the BIOS UI functions itself and preventing malicious users from booting the system from unauthorized peripheral devices.

The following diagram illustrates the relationships between system hardware, BIOS, operating system, and application program:




4-2 ENTERING SETUP

When system powered on, BIOS will enter the Power-On Self Test (POST) routines and displays below message on the screen:



POST screen

As long as this logo is present on the screen you may press the key (the one that shares the decimal point at the bottom of the number keypad) to enter the BIOS setup program. In a moment, the main menu of the AMI SETUP program will be shown on the screen:



Setup program initial screen

You may move the cursor by up/down keys to highlight the individual menu items. As you highlight each item, a brief description of the highlighted selection will appear at the bottom of the screen.

4-3. Main

BIOS SETUP UTILITY					
Main	Advanced	Boot	Security	Chipset	Exit
System Overview		Use [ENTER], [TAB] or [SHIFT-TAB] to select a field.			
AMIBIOS		Use [+] or [-] to configure system Time.			
Version	: 32520T00				
Build Date	: 04/03/12				
Processor					
Intel(R) Atom(TM) CPU	D525	@ 1.80GHz			
Speed	:1800MHz				
Count	: 1				
System Memory					
Size	: 1014MB				
System Time		[01:57:52]			
System Date		[Wed 04/29/2011]			
		←→	Select Screen		
		↓↑	Select Item		
		+ -	Change Field		
		Tab	Select Field		
		F1	General Help		
		F10	Save and Exit		
		ESC	Exit		
v02.68 (c)Copyright 1985-2009 American Megatrends, Inc.					

Main screen

Use <↑> or <↓> arrow keys to highlight the item and key in the value you want in each item. This menu provides basic system configurations, such as time and date.

AMI BIOS, Processor, System Memory

This items show the BIOS version, BIOS build up date, processor and system memory information of your system.


System Time

This setting allows you to set the system time. The format is [Hour: Minute: Second]. User can directly key-in value or use <+> or <-> arrow keys to increase/decrease it.

System Date

This setting allows you to set the system date. The format is [Day Month/ Date/ Year]. User can directly key-in value or use <+> or <-> arrow keys to increase/decrease it.


4-4. Advanced



Advanced screen

This menu provides advanced configurations such as CPU Configuration, IDE Configuration, SuperIO Configuration...etc.

4-4-1. CPU Configuration




CPU Configuration screen

This menu provides some information about CPU.

Hyper Threading Technology

Hyper Threading is Intel's term for its simultaneous multithreading implementation in their CPUs. Enable this function will improve parallelization of computation performed on PC microprocessor. For each processor core that is physically present, the operation system addresses two virtual processors, and shares the workload between them when possible.

4-4-2. IDE Configuration




IDE Configuration screen

This menu provides advanced IDE configuration for hard drive. The control items of SATA 1 / CF Card are all the same and describe in next section.

SATA 1/ CF Card

This setting displays the status of storages.

4-4-2.1 SATA 1 and CF Card



SATA 1 screen

Type

Select the type of device connected to the system.

LBA/Large Mode

Enabling LBA causes Logical Block Addressing to be used in place of Cylinders, Heads and Sectors.

Block (Multi-Sector Transfer)

Any selection except Disabled determines the number of sectors transferred per block.

PIO Mode

Configure the type of PIO (Programmed Input/Output) mode 0-4 for IDE device. Mode 0 through 4 provides successively increased performance.

DMA Mode

Select the type of Ultra DMA mode on a hard drive.


S.M.A.R.T

This allows you to activate the S.M.A.R.T. (Self-Monitoring Analysis & Reporting Technology) capability for the hard disks. S.M.A.R.T is a utility that monitors your disk status to predict hard disk failure. This gives you an opportunity to move data from a hard disk that is going to fail to a safe place before the hard disk becomes offline.

32Bit Data Transfer

Enables/Disables 32-bit data transfer.

4-4-3. SuperIO Configuration



SuperIO Configuration screen

*** WatchDog function**

If system hang or not respond for user, enable watchdog function can triggers a system reset by an user given value count down to zero.

Serial Port1~4 Address

Select IO address as serial ports default resource.

Serial Port1~4 IRQ

Select IO IRQ as serial ports default resource.

Parallel Port Address

Select IO address for parallel ports resource allocation.


Parallel Port Mode

Select the operation mode for parallel port.

Parallel Port IRQ

Select IRQ for parallel ports resource allocation.

4-4-4. Hardware Health Configuration



Hardware Health Configuration screen

System Temperature / CPU Temperature

Both section show System and CPU current temperature.


CPUFAN Speed

This item shows CPU fan speed.

VCORE / 12V / 5V / 1.05V / VSB

These items provide hardware health information.

4-4-5. APM Configuration



APM Configuration screen

Power Management/APM

This is the main control item for enable/disable below APM functions.

Power Button Mode

This setting controls shutdown action by pressing power button. The system will be shutdown immediately after pressing power button when set to “On/Off”. If set the power button mode to “Delay 4 seconds”, system will be shutdown after pressing and hold the power button over 4 seconds.

Restore on AC/Power Loss

Once a power failure situation happens, this item decides the system power state after AC power restore back.

Resume On RTC Alarm

When user set this option to [Enable], it allows system to be wake up at specific date/time.


RTC Alarm Date (Days)

Set a specific date value for RTC alarm function to wakeup system from soft off state.

System Time

Set a specific time value for RTC alarm function to wakeup system from soft off state.

4-4-6.USB Configuration



USB Configuration screen

Legacy USB Support

Set to [Enabled] if you want to use USB device in the legacy operating system, such as MS-DOS or SCO Unix.


USB 2.0 Controller Mode

Configure the onboard USB 2.0 controller operation mode to high Speed or full speed mode.

USB Beep Message

System will generate beep sound during USB device enumeration.

4-4-6.1 USB Mass Storage Device Configuration




USB Mass Storage Device Configuration screen

Emulation Type

Select which type of device that USB mass storage emulation. When user select to [Auto], the USB storage size less than 530MB will be emulated as floppy drive and remaining as hard drive.

4-5. Boot




Boot screen

This menu provides control items for system boot configuration.

PXE Support

This is the main control item for enable/disable PXE (Preboot Execution Environment) support.

4-5-1 Boot Settings Configuration



Boot Settings Configuration screen

Quick Boot

Enable this item allows BIOS POST to skip some tests during boot-up for saving boot time.


Quiet Boot

When set this option to [disabled], BIOS will display normal POST messages.

Parity Check

This setting enables or disables memory or parity error check.

4-5-2 Boot Device Priority




Boot Device Priority screen

1st / 2nd / 3rd ...Boot Device

Choose the boot sequence from the available devices..

4-5-3 Boot Device Priority




Hard Disk Drives screen

1st / 2nd ...Drive

This setting allows user to set the priority of hard drive or another bootable USB storages. Press <Enter> to enter the sub-menu and press <↑> or <↓> arrow keys to select the device. Another way is to press <+> or <-> to move it up/down in the priority list.

4-6. Security Settings



Security Settings screen


Change Supervisor Password

Supervisor Password controls the access right to the BIOS Setup utility. These settings allow user to set or change the supervisor password.

Change User Password


User Password controls system access right when power on. These settings allow user to set or change the user password.

4.7 Chipset




Advanced Chipset Settings screen

4-7-1 North Bridge Chipset Configuration



North Bridge Chipset Configuration screen

4-7-1.1 Video Function Configuration



Video Function Configuration screen

DVMT Mode Select / DVMT/FIXED Memory

Intel's Dynamic Video Memory Technology (DVMT) allows the system to dynamically allocated memory resources according to the demands of the system at any point in time. The key idea in DVMT is to improve the efficiency of the memory allocated to either system or graphics processor. It is recommended that you set this BIOS feature to DVMT Mode for maximum performance. Setting it to DVMT Mode ensures that system memory is dynamically allocated for optimal balance between graphics and system performance.


Boot Display Device

Choose the default boot display device by user requirement such as [CRT], [LVDS] and [CRT+LVDS]

Flat Panel Type

Select the resolution for the connected LVDS panel such as [800x600] and [1024x768].

4-7-2 South Bridge Configuration



South Bridge Chipset Configuration screen


USB 2.0 Controller

Enable or disable the USB 2.0 Controller.

HDA Controller

Enable or disable the onboard High-definition Audio controller.

4.8 Exit



Exit screen

Save Changes and Exit

Save changes to CMOS and then exit the BIOS setup screen. User can also press the [F10] key for this operation.

Discard Changes and Exit


Abandon all changes and exit the BIOS setup screen. User can also press the [ESC] key for this operation.

Discard Changes

Discard all changes done so far to the setup items. User can press the [F7] key for this operation.

Load Optimal Defaults

Press <Enter> on this item, it will show a confirmation dialog box with a message like below:



Pressing "Ok" to loads the factory recommended optimal setting for system operations. User can also press the [F9] key for this operation.


Load Failsafe Defaults

Press <Enter> on this item, it will show a confirmation dialog box with a message like below:



To use the BIOS failsafe default values, change the prompt to "Ok" and press the <Enter> key. User can also press the [F8] key for this operation.

SYSTEM ASSEMBLY




This appendix contains exploded diagrams and part numbers of the PA-3252 system.

Sections included:

- Exploded Diagram for PA-3252 Top Case
- Exploded Diagram for PA-3252 Open & Close
- Exploded Diagram for PA-3252 Bottom Case
- Exploded Diagram for PA-3252 Inside Box
- Exploded Diagram for PA-3252 CPU Cooler
- Exploded Diagram for PA-3252 LCD Panel
- Exploded Diagram for PA-3252 Printer Box
- Exploded Diagram for PA-3252 2 Inch Printer
- Exploded Diagram for PA-3252 2 Inch Printer Cover



- Exploded Diagram for PA-3252 3 Inch Printer
- Exploded Diagram for PA-3252 3 Inch Printer Cover
- Exploded Diagram for PA-3252 Printer Control Board
- Exploded Diagram for PA-3252 Hard Disk Drive
- Exploded Diagram for PA-3252 VFD Cover
- Exploded Diagram for PA-3252 SSD Module
- Exploded Diagram for PA-3252 System FAN
- Exploded Diagram for PA-3252 RFID Module
- Exploded Diagram for PA-3252 Memory Maintenance
- Exploded Diagram for PA-3252 Mini PCIe and CF Card Maintenance
- Exploded Diagram for PA-3252 2 Inch Printer Maintenance
- Exploded Diagram for PA-3252 3 Inch Printer Maintenance
- Exploded Diagram for PA-3252 Printer Platen Block Maintenance

EXPLODED DIAGRAM FOR PA-3252 TOP CASE




NO.	COMPONENT NAME	PART NO.	Q'TY
1	SCREW	22-272-40004311	2
2	SCREW	22-242-30005311	2
3	PULLER	30-080-04100000	1
4	INSIDE BOX TOP COVER	20-004-03001199	1
5	T CASE-B CASE ASSY	**-***-*****	1
6	HDD ASSY	**-***-*****	1

EXPLODED DIAGRAM FOR PA-3252 OPEN & CLOSE




NO.	COMPONENT NAME	PART NO.	Q'TY
1	TOP CASE ASSY	**-*-*-*****	1
2	OPEN CLOSED BUSHING	30-026-0430000	2
3	BOTTOM CASE ASSY	**-*-*-*****	1

EXPLODED DIAGRAM FOR PA-3252 BOTTOM CASE




NO.	COMPONENT NAME	PART NO.	Q'TY
1	FAN ASSY	**-*-*****	1
2	PORON	90-013-15200181	1
3	SWITCH CAP	30-001-28100099	1
4	SCREW	22-272-20004011	2
5	WIRELESS CARD ASSY	**-*-*****	1
6	FOOT	22-289-60035007	2
7	SPEAKER	13-500-08280018	1
8	MINI PCI DOOR	30-007-28110199	1
9	POWER COVER	30-002-28210199	1
10	IO COVER	30-002-28110199	1
11	SATA HDD CABLE	27-012-16504081	1
12	SCREW	22-242-30005311	2
13	INSIDE BOX ASSY 1	**-*-*****	1

EXPLODED DIAGRAM FOR PA-3252 INSIDE BOX




NO.	COMPONENT NAME	PART NO.	Q'TY
1	HEAT SINK	21-002-11564002	1
2	COM CABLE	27-024-16502031	1
3	RAM	***-***-*****	1
4	No.4 Boss	22-692-40048051	8
5	SCREW	22-242-30005311	6
6	INSIDE BOX ASSY 2	***-***-*****	1




NO.	COMPONENT NAME	PART NO.	Q'TY
1	PCBA	PB-3151	1
2	BOTTOM CASE	30-001-28110220	1
3	CANOE CLIP	30-076-04200000	2
4	RUBBER FOOT	30-004-01500000	2
5	THERMAL PAD	21-006-82020002	1
6	SNAP BUSHING	30-026-04100008	1
7	WIRELESS ANTENA	27-029-00003072	1
8	ROLLER PIN	20-045-19012199	2
9	ROLLER	30-041-04100165	2
10	INSIDE BOX ASSY	20-040-03001236	1

EXPLODED DIAGRAM FOR PA-3252 CPU COOLER




NO.	COMPONENT NAME	PART NO.	Q'TY
1	FAN BRACKET	20-006-03001213	1
2	FAN	21-004-04545151	1
3	SCREW	22-232-25004011	2

EXPLODED DIAGRAM FOR PA-3252 LCD PANEL




NO.	COMPONENT NAME	PART NO.	Q'TY
1	CABLE TIE	30-015-04200000	3
2	LVDS CABLE	27-020-21007111	1
3	INVERTER CABLE	27-015-21006111	1
4	FLAT RESISTIVE TOUCH PANEL	52-380-00114701	1
5	LCD BACK COVER RUBBER	30-013-06100124	1
6	INVERTER MYLAR	90-056-35100210	1
7	LED CABLE	27-018-21003071	1
8	FRONT COVER	30-003-28110220	1
9	TOP COVER HINHE	30-002-09130220	3
10	LED LENS	30-021-02130220	1
11	BACK COVER	30-003-28210220	1
12	LED HOUSING	30-014-04100165	1
13	LCD INVERTER	52-101-15020503	1
14	EMI SPONGE	90-050-31100000	2
15	DOUDLE COATED TAPE-B	94-026-04902220	2
16	DOUDLE COATED TAPE-A	94-026-04901220	2
17	TOUCHSCREEN EXTENDING CABLE	27-043-22003071	1
18	SCREW	22-242-30005311	3
19	SCREW	22-125-30012061	12
20	PORON	30-013-24100000	4
21	PANEL HOLDER	20-029-03001220	1
22	15" LCD PANEL	***-***-*****	1
23	SCREW	22-232-30060211	6

EXPLODED DIAGRAM FOR PA-3252 PRINTER BOX




NO.	COMPONENT NAME	PART NO.	Q'TY
1	SCREW	22-222-30004011	3
2	SCREW	22-242-30005311	3
3	BOTTOM CASE ASSY 2	**-***-*****	1
4	PRINTER_ASSY	**-***-*****	1

EXPLODED DIAGRAM FOR PA-3252 2 INCH PRINTER




NO.	COMPONENT NAME	PART NO.	Q'TY
1	EMI SHIELDING GASKET	90-050-31100000	1
2	PRINTER 2IN PAPER WALL	30-002-28310199	1
3	3IN SIDE WALL R	30-002-28610199	1
4	PRINTER ADD ARM	30-002-09110199	1
5	PRINTER COVER SPRING R	23-000-00000502	1
6	SCREW	22-272-20004011	3
7	2IN PRINTER MOUDULE A	52-701-00020003	1
8	PRINTER COVER SPRING L	23-000-01000502	1
9	SCREW	22-242-30005311	3
10	PAPER COVER PIN	20-045-19011199	1
11	2IN PRINTER COVER ASSY	***-***-*****	1
12	PRINTER BOX3 ASSY	20-040-03002199	1
13	ROTARY DAMPER	30-002-09110000	1

EXPLODED DIAGRAM FOR PA-3252 2 INCH PRINTER COVER




NO.	COMPONENT NAME	PART NO.	Q'TY
1	SCREW	22-122-30080011	2
2	PRINTER DOOR	30-007-28210199	1
3	PAPER HOLDER	30-012-02110165	1
4	SCREW	22-125-20008011	2
5	2IN PRINTER MOUDULE B	52-701-00020003	1

EXPLODED DIAGRAM FOR PA-3252 3 INCH PRINTER




NO.	COMPONENT NAME	PART NO.	Q'TY
1	EMI SHIELDING GASKET	90-050-31100000	1
2	PRINTER COVER SPRING R	23-000-00000502	1
3	PRINTER COVER SPRING L	23-000-01000502	1
4	3IN SIDE WALL R	30-002-28610199	1
5	3IN SIDE WALL L	30-002-28710199	1
6	SCREW	22-272-20004011	4
7	3IN PRINTER MOUDULE A	52-701-00017003	1
8	SCREW	22-242-30005311	3
9	PAPER COVER PIN	20-045-19011199	1
10	PRINTER ADD ARM	30-002-09110199	1
11	PRINTER BOX3 ASSY	20-040-03002199	1
12	ROTARY DAMPER	30-002-09110000	1
13	3IN PRINTER COVER ASSY	***-***-*****	1

EXPLODED DIAGRAM FOR PA-3252 3 INCH PRINTER COVER




NO.	COMPONENT NAME	PART NO.	Q'TY
1	SCREW	22-122-30080011	2
2	PRINTER DOOR	30-007-28210199	1
3	PAPER HOLDER	30-012-02110165	1
4	SCREW	22-125-20008011	2
5	3IN PRINTER MOUDULE B	52-701-00017003	1

EXPLODED DIAGRAM FOR PA-3252 PRINTER CONTROL BOARD




NO.	COMPONENT NAME	PART NO.	Q'TY
1	SCREW	22-272-20004011	4
2	SCREW	22-272-30004318	2
3	PRINTER POWER CABLE	27-012-16502071	1
4	PRINTER USB CABLE	27-006-16503111	1
5	PRINTER PCB COVER	20-004-03001165	1
6	PRINTER PCB	52-701-00237003	1
7	SCREW	22-232-25004011	2
8	BOTTOM CASE ASSY 1	**-***-*****	1
9	VFD COVER ASSY	**-***-*****	1

EXPLODED DIAGRAM FOR PA-3252 HARD DISK DRIVE




NO.	COMPONENT NAME	PART NO.	Q'TY
1	THERMAL PAD	21-006-84535001	1
2	SCREW	22-272-30004318	4
3	HDD	SEE ORDER	1
4	HDD HOLDER	20-029-01001165	1

EXPLODED DIAGRAM FOR PA-3252 VFD COVER




NO.	COMPONENT NAME	PART NO.	Q'TY
1	VFD MOUDULE	52-901-17001703	1
2	PRINTER EJECTOR WITH PRINTER	30-002-28410199	1
3	VFD LENS	30-021-02130199	1
4	VFD COVER	30-002-28910199	1




NO.	COMPONENT NAME	PART NO.	Q'TY
1	VFD COVER	30-002-28910199	1
2	PRINTER EJECTOR WO PRINTER	30-002-28510199	1

EXPLODED DIAGRAM FOR PA-3252 SSD MODULE




NO.	COMPONENT NAME	PART NO.	Q'TY
1	SSD MODULE	***-***-*****	1
2	SSD BRACKET	80-006-03001199	1
3	SSD BRACKET MYLAR	90-056-05200181	1
4	SCREW	22-222-16003015	4
5	SSD COVER MYLAR	90-056-25100000	1

EXPLODED DIAGRAM FOR PA-3252 RFID MODULE





NO.	COMPONENT NAME	PART NO.	Q'TY
1	RFID CABLE	27-068-19907111	1
2	RFID MODULE	52-151-08321015	1
3	SCREW	22-272-20004011	2
4	SCREW	22-242-30005311	1
5	RFID BRACKET	20-006-03002220	1

EXPLODED DIAGRAM FOR PA-3252 MEMORY MAINTENANCE




EXPLODED DIAGRAM FOR PA-3252 MINI PCIE AND CF CARD MAINTENANCE










NO.	COMPONENT NAME	PART NO.	Q'TY
1	WIRELESS LEN CARD HOLDER	80-029-03001165	1
2	WIRELESS LEN CARD	52-151-02116004	1
3	SCREW	22-272-20004011	2



EXPLODED DIAGRAM FOR PA-3252 2 INCH PRINTER MAINTENANCE




EXPLODED DIAGRAM FOR PA-3252 3 INCH PRINTER MAINTENANCE



EXPLODED DIAGRAM FOR PA-3252 PRINTER PLATEN BLOCK MAINTENANCE



TECHNICAL SUMMARY




This section will give you a brief introduction of the allocation maps for the system resources.

Sections included:

- Block Diagram
- Interrupt Map
- DMA Channels Map
- I / O Map
- Watchdog Timer Configuration
- Flash BIOS Update

BLOCK DIAGRAM



INTERRUPT MAP

IRQ	ASSIGNMENT
0	System Timer
1	Standard 101/102-Key or Microsoft Natural PS/2 Keyboard
3	Communications Port (COM2)
4	Communications Port (COM1)
5	Intel(R) ICH8 Family SMBus Controller - 283E
8	System CMOS/real time clock
9	Microsoft ACPI-Compliant System
10	Communications Port (COM4)
11	Communications Port (COM3)
12	Microsoft PS/2 Mouse
13	Numeric data processor
14	Primary IDE Channel
16	Intel(R) Graphics Media Accelerator 3150
16	Intel(R) ICH8 Family USB Universal Host Controller - 2834
17	Realtek PCIe GBE Family Controller
18	Intel(R) ICH8 Family USB2 Enhanced Host Controller - 283A
18	Intel(R) ICH8 Family USB Universal Host Controller - 2832
18	Intel(R) ICH8M 3 port Serial ATA Storage Controller - 2828
19	Intel(R) ICH8 Family USB Universal Host Controller - 2831
21	Intel(R) ICH8 Family USB Universal Host Controller - 2835
21	Microsoft UAA Bus Driver for High Definition Audio
22	Intel(R) ICH8 Family PCI Express Root Port 1 - 283F
23	Intel(R) ICH8 Family PCI Express Root Port 6 - 2849
23	Intel(R) ICH8 Family USB Universal Host Controller - 2830
23	Intel(R) ICH8 Family USB2 Enhanced Host Controller - 2836

DMA CHANNELS MAP

DMA CHANNEL	ASSIGNMENT
4	Direct memory access controller

I/O MAP

I/O MAP	ASSIGNMENT
0x00000000-0x00000CF7	PCI bus
0x00000000-0x00000CF7	Direct memory access controller
0x00000010-0x0000001F	Motherboard resources
0x00000020-0x00000021	Programmable interrupt controller
0x00000022-0x0000003F	Motherboard resources
0x00000040-0x00000043	System timer
0x00000044-0x0000005F	Motherboard resources
0x00000060-0x00000060	Standard 101/102-Key or Microsoft Natural PS/2 Keyboard
0x00000061-0x00000061	System speaker
0x00000062-0x00000063	Motherboard resources
0x00000064-0x00000064	Standard 101/102-Key or Microsoft Natural PS/2 Keyboard
0x00000065-0x0000006F	Motherboard resources
0x00000070-0x00000071	System CMOS/real time clock
0x00000072-0x0000007F	Motherboard resources
0x00000080-0x00000080	Motherboard resources
0x00000081-0x00000083	Direct memory access controller
0x00000084-0x00000086	Motherboard resources
0x00000087-0x00000087	Direct memory access controller
0x00000088-0x00000088	Motherboard resources
0x00000089-0x0000008B	Direct memory access controller
0x0000008C-0x0000008E	Motherboard resources
0x0000008F-0x0000008F	Direct memory access controller
0x00000090-0x0000009F	Motherboard resources
0x000000A0-0x000000A1	Programmable interrupt controller
0x000000A2-0x000000BF	Motherboard resources
0x000000C0-0x000000DF	Direct memory access controller
0x000000E0-0x000000EF	Motherboard resources
0x000000F0-0x000000FF	Numeric data processor
0x000001F0-0x000001F7	Primary IDE Channel

Appendix B Technical Summary

I/O MAP	ASSIGNMENT
0x00000274-0x00000277	ISAPNP Read Data Port
0x00000279-0x00000279	ISAPNP Read Data Port
0x00000378-0x0000037F	Printer Port (LPT1)
0x000003B0-0x000003BB	Intel(R) Graphics Media Accelerator 3150
0x000003C0-0x000003DF	Intel(R) Graphics Media Accelerator 3150
0x000003E8-0x000003EF	Communications Port (COM3)
0x000003F6-0x000003F6	Primary IDE Channel
0x000003F8-0x000003FF	Communications Port (COM1)
0x00000400-0x0000041F	Intel(R) ICH8 Family SMBus Controller - 283E
0x000004D0-0x000004D1	Motherboard resources
0x00000500-0x0000053F	Motherboard resources
0x00000800-0x0000087F	Motherboard resources
0x00000A00-0x00000A0F	Motherboard resources
0x00000A00-0x00000A0F	Motherboard resources
0x00000D00-0x0000FFFF	PCI bus
0x0000C080-0x0000C087	Intel(R) Graphics Media Accelerator 3150
0x0000C400-0x0000C41F	Intel(R) ICH8 Family USB Universal Host Controller - 2835
0x0000C480-0x0000C49F	Intel(R) ICH8 Family USB Universal Host Controller - 2834
0x0000C800-0x0000C81F	Intel(R) ICH8 Family USB Universal Host Controller - 2832
0x0000C880-0x0000C89F	Intel(R) ICH8 Family USB Universal Host Controller - 2831
0x0000CC00-0x0000CC1F	Intel(R) ICH8 Family USB Universal Host Controller - 2830
0x0000D080-0x0000D08F	Intel(R) ICH8M 3 port Serial ATA Storage Controller - 2828
0x0000D400-0x0000D40F	Intel(R) ICH8M 3 port Serial ATA Storage Controller - 2828
0x0000D480-0x0000D483	Intel(R) ICH8M 3 port Serial ATA Storage Controller - 2828
0x0000D800-0x0000D807	Intel(R) ICH8M 3 port Serial ATA Storage Controller - 2828
0x0000D880-0x0000D883	Intel(R) ICH8M 3 port Serial ATA Storage

I/O MAP	ASSIGNMENT
	Controller - 2828
0x0000DC00-0x0000DC07	Intel(R) ICH8M 3 port Serial ATA Storage Controller - 2828
0x0000E000-0x0000EFFF	Intel(R) ICH8 Family PCI Express Root Port 6 - 2849
0x0000E800-0x0000E8FF	Realtek PCIe GBE Family Controller
0x0000FFA0-0x0000FFAF	Intel(R) ICH8M Ultra ATA Storage Controllers - 2850

WATCHDOG TIMER CONFIGURATION

Watchdog timer can be configured via I/O port address 2E (hex) and 2F (hex). 2E (hex) is the address port. 2F (hex) is the data port. User can assign the target offset by writing value into address port 2E (hex) and then write/read data to/from the target offset by data port 2F (hex).

Configuration Sequence

Please follow the following steps to program W83627UHG configuration registers.

1. Enter the extended function mode.
2. Configure the configuration registers.
3. Exit the extended function mode.

1. Enter the extended function mode

To place W83627UHG into the Extended Function Mode, two successive writes of 0x87 must be applied to Extended Function Enable Registers (EFERs, i.e. 2Eh or 4Eh).

2. Configure the configuration registers

User must select to the desired Logical Device number and activates the desired Logical Devices through Extended Function Index Register (EFIR) and Extended Function Data Register (EFDR). The EFIR is located at the same address as the EFER, and the EFDR is located at address (EFIR+1). First, write the Logical Device Number (i.e. 0x07) to the EFIR and then write the number of the desired Logical Device to the EFDR. If accessing the Chip (Global) Control Registers, this step is not required. Secondly, write the address of the desired configuration register within the Logical Device to the EFIR and then write (or read) the desired configuration register through the EFDR.

3. Exit the extended function mode

To exit the Extended Function Mode, writing 0xAA to the EFER is required. Once SuperIO exits the Extended Function Mode, it goes back to the normal running mode.

Code example for watch dog timer

Enable watchdog timer and set timeout interval to 30 seconds.

```
;----- Enter to extended function mode -----  
mov    dx,    2Eh  
mov    al,    87h  
out    dx,    al  
out    dx,    al  
;----- Select Logical Device 8 of watchdog timer -----  
mov    al,    07h  
out    dx,    al  
inc    dx  
mov    al,    08h  
out    dx,    al  
;----- Logic device activation for watch dog timer -----  
dec    dx  
mov    al,    030h  
out    dx,    al  
inc    dx  
mov    al,    01h  
out    dx,    al  
;----- Set second as counting unit -----  
dec    dx  
mov    al,    0F5h  
out    dx,    al  
inc    dx  
in     al,    dx  
and    al,    not 08h  
out    dx,    al  
;----- Set timeout interval as 30seconds and start counting -----  
dec    dx  
mov    al,    0F6h  
out    dx,    al  
inc    dx  
mov    al,    30  
out    dx,    al  
;----- Exit the extended function mode -----  
dec    dx  
mov    al,    0AAh  
out    dx,    al
```


FLASH BIOS UPDATE

I. Before System BIOS update

1. Prepare a bootable media (ex. USB storage device) which can boot system to DOS prompt.
2. Download and save the BIOS ROM (ex. [32520T00.rom](#)) file to the bootable device.
3. Copy AMI flash utility – AFUDOS.exe (v4.38) into bootable device.


```
C:\AFUDOS>dir

Volume in drive C is JASON
Volume Serial Number is 56AD-41D6
Directory of C:\AFUDOS

.                <DIR>                08-25-11  2:17p
..               <DIR>                08-25-11  2:17p
AFUDOS  EXE           154,416  01-25-11  4:05p
AFUDOS  TXT             13,066  01-25-11  4:05p
32520T00 ROM      1,048,576  04-03-12  9:49a
        3 file(s)          1,216,058 bytes
        2 dir(s)          631,111,680 bytes free

C:\AFUDOS>_
```

4. Make sure the target system can first boot to the bootable device.
 - a. Connect the bootable USB device.
 - b. Turn on the system and press key during BIOS POST procedure.
 - c. System will go into the BIOS setup menu.
 - d. Select [Boot] menu.
 - e. Select [Boot Devices Priority] sub-menu, set the USB bootable device to be the 1st boot device.
 - f. Pressing <F10> key to save configuration and exit the BIOS setup menu.



II. AFUDOS command for system BIOS update

AFUDOS.exe is the AMI firmware update utility, the command line is shown as below:

AFUDOS <ROM File Name> [option1] [option2]....

User can type “AFUDOS/?” to see all the definition of each control options. The recommend option for BIOS ROM update include following parameters:

- /P**: Program main BIOS image.
- /B**: Program Boot Block.
- /N**: Program NVRAM.
- /C**: Destroy CMOS checksum
- /X**: Don't check ROM ID.

III. BIOS update procedure

1. Use the bootable USB storage to boot up system into the DOS command prompt.
2. Type "**AFUDOS 3252xxxx.ROM /P /B /N /C /X** " and press enter to start the flash procedure.
(Note that **xxxx** means the BIOS revision part, ex. 0P01...)
3. During the update procedure, you will see the BIOS update process status and its percentage. Beware! Do not turn off system power or reset your computer if the whole procedure are not complete yet, or it may crash the BIOS ROM and make system unable to boot up next time.
4. After BIOS update procedures complete, the messages should be like the figure shown below.

```
C:\AFUDOS>afudos 32520T00.ROM /P /B /N /C /X
+-----+
|                AMI Firmware Update Utility  v4.38                |
|      Copyright (C)2010 American Megatrends Inc. All Rights Reserved.  |
+-----+
- Boothblock checksum ... ok
- Module checksums ..... ok
- Erasing flash ..... done
- Writing flash ..... done
- Verifying flash ..... done
- Erasing NURAM ..... done
- Writing NURAM ..... done
- Verifying NURAM ..... done
- Erasing Boothblock .... done
- Writing Boothblock .... done
- Verifying Boothblock ... done
- CMOS checksum destroyed
- Program ended normally.
C:\AFUDOS>_
```

5. User can restart the system and boot up with new BIOS now.